HL-L5200DW



Print

Brother Mono Laser Printer

The ultra reliable mono laser printer

Ideal for:



Built with the busy office in mind

This wireless and networked device offers fast print speeds and excellent paper handling options. You can also reduce your print spend with optional high-yield toner cartridges, making this machine the ideal print partner for your office.

Top Features:

Fast print speeds of up to 40ppm

Combined paper input of 300 sheets

Automatic 2-sided printing

High-yield replacement cartridges -Optional high-yield 8,000¹ page toner cartridge

1 line, 16 character backlit LCD display

High speed wired (10Base-T/100Base-TX) and wireless (IEEE 802.11b/g/n) network interfaces

USB 2.0 connectivity

Wi-Fi Direct



Increase productivity levels

- Productivity is increased significantly thanks to fast print speeds of up to 40ppm
- Maximise performance with high-speed wired (10Base-T/100Base-TX) and wireless (IEEE 802.11b/g/n) network interface
- Easily print from mobile devices using the Brother iPrint&Scan app, Android print service plugin, Google Cloud Print 2.0, Mopria and AirPrint
- The easy to use 1 line, 16 character backlit LCD display, enables you to print with no complications

Complete peace of mind

- New build technology gives complete reliability, enabling you to print up to 3,500 pages per month
- Outstanding paper handling options with a standard paper input capacity of 300 sheets expandable to 1,340 sheets and a standard 150 sheet output tray

Exceptionally low running costs

- Designed for the busy office, the HL-L5200DW includes a 3,000¹ page toner cartridge and can take an optional 8,000¹ page toner cartridge to lower your running costs even further
- A range of solutions under the PrintSmart umbrella can help you reduce your print spend such as PrintSmart Cost Control

Meeting your IT challenges

 This range gives you the highest levels of security, featuring Secure Function lock 3.0, Active directory connectivity and Internet Protocol Security (IPsec).
 Plus, the range also features Print Archive, Secure Reset and Certificate Management



General

Technology	Electrophotographic Laser Printer
Laser Classification	Class 1 Laser Product (IEC60825-1:2007)
Processor	Cortex-A9 800MHz
Memory	256MB
Local Interface	Hi-Speed USB 2.0
Control Panel	1 line, 16 character backlit LCD display
Wired Network Interface	10Base-T/100Base-TX
Wireless Network Interface	IEEE 802.11b/g/n
Print	
Print Speed Standard (A4)	Up to 40ppm (pages per minute)
Print Speed 2-Sided (A4)	Up to 20 sides per minute (10 sheets per minute)
Resolution	Up to 1,200 x 1,200 dpi
Quiet Mode	A mode to reduce the printing noise by reducing the print speed to 25ppm
FPOT (First Print Out Time)	Less than 7.2 seconds from ready mode
Automatic 2-Sided Printing	Print on to both sides of the paper
Print Languages	PCL6, BR-Script3 (PostScript [®] 3™ Language Emulation), IBM Proprinter XL, Epson FX-850 PDF version1.7, XPS version 1.0
Embedded Fonts (PCL)	66 scalable fonts, 12 bitmap fonts, 13 barcodes
Embedded Fonts (Postscript)	66 scalable fonts
Embedded Barcodes (PCL)	Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C)
Printer Functions	
N-up Printing ³	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)
Poster Printing⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages
Poster Printing⁴ Watermark Printing⁴	Enlarge 1 A4 page into a poster using 4, 9,
-	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages Watermark your documents with pre-defined
Watermark Printing⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages Watermark your documents with pre-defined text or with your own user-defined messages Add identification to your printed documents (date & time, short custom message or
Watermark Printing⁴ ID Printing⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages Watermark your documents with pre-defined text or with your own user-defined messages Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided printing (recommended for media not
Watermark Printing ⁴ ID Printing ⁴ Manual 2-Sided Print ⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages Watermark your documents with pre-defined text or with your own user-defined messages Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided printing (recommended for media not supported by automatic 2-sided print) Print documents in A5 booklet format using
Watermark Printing ⁴ ID Printing ⁴ Manual 2-Sided Print ⁴ Booklet Printing ⁴	 Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages Watermark your documents with pre-defined text or with your own user-defined messages Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided printing (recommended for media not supported by automatic 2-sided print) Print documents in A5 booklet format using automatic or manual 2-sided print Ignores any blank pages in your documents by not printing them
Watermark Printing ⁴ ID Printing ⁴ Manual 2-Sided Print ⁴ Booklet Printing ⁴ Skip Blank Page ⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages Watermark your documents with pre-defined text or with your own user-defined messages Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided printing (recommended for media not supported by automatic 2-sided print) Print documents in A5 booklet format using automatic or manual 2-sided print Ignores any blank pages in your documents by not printing them Store your favourite driver settings as profiles
Watermark Printing ⁴ ID Printing ⁴ Manual 2-Sided Print ⁴ Booklet Printing ⁴ Skip Blank Page ⁴ Print Profiles ³	 Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages Watermark your documents with pre-defined text or with your own user-defined messages Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided printing (recommended for media not supported by automatic 2-sided print) Print documents in A5 booklet format using automatic or manual 2-sided print Ignores any blank pages in your documents by not printing them Store your favourite driver settings as profiles to easily recall them Converts all text in your documents to black
Watermark Printing ⁴ ID Printing ⁴ Manual 2-Sided Print ⁴ Booklet Printing ⁴ Skip Blank Page ⁴ Print Profiles ³ Print Text In Black ⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages Watermark your documents with pre-defined text or with your own user-defined messages Add identification to your printed documents (date & time, short custom message or PC username) Manual 2-sided printing (recommended for media not supported by automatic 2-sided print) Print documents in A5 booklet format using automatic or manual 2-sided print Ignores any blank pages in your documents by not printing them Store your favourite driver settings as profiles to easily recall them Converts all text in your documents to black when printed An electronic carbon copy feature that saves an electronic copy of all printed documents

Printer Driver

Windows®	Windows® 10 (32 & 64 bit editions) Windows® 8 (32 & 64 bit editions) Windows® 7 (32 & 64 bit editions) Windows Vista® (32 & 64 bit editions) Windows® XP Professional (32 & 64 bit editions) Windows® XP Home Windows® Server 2012, 2012R2 & 2008R2 Windows® Server 2008 (32 & 64 bit editions) Windows® Server 2003 (32 & 64 bit editions)
Macintosh ⁵	OS X 10.8.5, 10.9.x, 10.10.x, 10.11.x
Linux⁵	CUPS, LPD/LPRng (32 & 64 bit editions)
PostScript Universal Printer Driver	Driver for Windows [®] that enables you to print to any network or locally-connected Brother laser printer that supports PostScript
PCL Driver	Universal PCL5e generic driver
Fleet Management Too	ols
Unattended Installer ⁴	Ability to centrally deploy and customise our drivers and software
MSI Installer⁴	Modular installers that can be distributed through Active Directory®
Embedded Web Server	Web based print management software embedded onto the device
BRAdmin Professional 3485	LAN/WAN management software
Driver Deployment Wizard ⁴	Easily create print drivers for hassle free deployment over your network
Paper Handling	
Standard Paper Input ²	Lower Tray - 250 sheets Multi Purpose Tray - 50 sheets
Optional Paper Input ²	250 sheet tray (LT-5500) 520 sheet tray (LT-6500) Maximum of 2 optional trays (LT-5500 & LT-6500 can be used together)
Paper Output ²	Face Down - 150 sheets Face Up (Straight Paper Path) - 1 sheet
Media Specification	
Media Types & Weights ⁷	Standard & Optional Trays - plain, recycled, coloured and letterhead paper (between 60 - 120g/m ²) Multi Purpose Tray - plain, recycled, bond, coloured and letterhead paper (between 60 - 200g/m ²) 2-Sided Print - plain, recycled, coloured and letterhead paper (between 60 - 105g/m ²)
Envelope & Label Printing	Yes, from the Multi Purpose Tray: support for 10 envelopes up to 10mm total thickness
Media Sizes	Standard Tray - A4, Letter, A5, A5 (Long Edge), A6, Executive, Legal, Folio, Mexico Legal, India Legal Optional Tray - A4, Letter, A5, Executive, Legal, Folio, Mexico Legal, India Legal Multi Purpose (MP) Tray - Width: 76.2mm to 215.9mm x Length: 127mm to 355.6mm 2-Sided Print - A4
PrintSmart Solutions (Optional)
PrintSmart CostControl	Monitor and control printing costs for all Brother and 3rd party devices
For more information on PrintS	Smart Solutions visit www.brother.eu
Dimensions & Weights	3
With Carton (WxDxH)	485 x 450 x 377mm 13kg
Without Carton (WxDxH)	373 x 388 x 255mm 10.7kg

1 Approx declared yield value in accordance with ISO/IEC19752.
2 Calculated with 80g/m² paper.
3 Windows[®] & Mac[®] only.
4 Windows[®] only.
5 Optional free download from the Brother Solutions Centre http://support.brother.com
6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.
7 It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m².



Network & Security

Network & Security	
Wired Network	Built in Ethernet 10Base-T/100Base-TX
Network Protocols	TCP/IP (IPv4 and IPv6)
Wireless Network	IEEE 802.11b/g/n (Infrastructure Mode / Adhoc Mode)
Wi-Fi Direct™	Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)
Wireless Set-Up Support	Wi-Fi Protected Setup (WPS)
Wireless Applications	Vertical Pairing
IPv4	ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/ LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP Client and server, SMTP Client, SNMPv1/v2c/ v3, ICMP, Web Services (Print), CIFS client, SNTP client
IPv6 (off by default)	NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c, ICMPv6, Web Services (Print), CIFS Client, SNTP Client
Wired Network Security	SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3, Kerberos, IPsec, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS)
Wireless Network Security	WEP 64/128 bit, WPA-PSK, (TKIP/AES), WPA2-PSK (AES), SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP- TTLS), Kerberos, IPSec
Print Log To Network⁴	Records printing activities from each individual user, including network username, name of document printed and number of pages, to a file on a network
E-mail Notifications	Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing
E-mail Reports	Receive usage reports on a regular basis via e-mail
IP Filter	Restrict which network users can or cannot access the device over the network (IPv4 only)
Secure Function Lock 3.0	Restrict printing activity to individual or groups of users over a network. Can be used with PC User Login Name for up to 100 users
Secure Print ³	Protect print jobs with a 4 digit release code required at the device in order for them to be printed
Setting Lock	Secures access to the devices control panel by locking it
Duty Cycles	
Duty Cycles	
Recommended Monthly	Up to 3,500 pages monthly print volume

Mobile / Web Based Printing

Web based F	mung
Brother iPrint&Scan (Android)	Print and check the machine status from an Android device
Brother iPrint&Scan (iPad / iPhone / iPod)	Print and check the machine status from an iPad / iPhone / iPod Touch
Brother iPrint&Scan (Windows [®] Phone)	Print directly from a smart phone running the Windows® Phone Operating System
Brother iPrint&Scan (Windows [®] 8 & RT)	Print directly from a Windows [®] 8 or Windows RT Tablet
Google Cloud Print 2.0	Print most common file types from any Google Cloud Print enabled application
AirPrint	Print most common file types from any AirPrint enabled application
Mopria	Print most common file types from Mopria supported Android devices
Android Print Service Plugin	Print from Android devices without a dedicated App
Supplies & Accessorie	es
Inbox Toner	3,000 pages ¹
Standard Yield Toner	3,000 pages ¹ (TN-3430)
High Yield Toner	8,000 pages ¹ (TN-3480)
Drum (DR-3400)	Approx. 50,000 pages at 3 pages per job Approx. 30,000 pages at 1 page per job
LT-5500	250 sheet optional paper input tray
LT-6500	520 sheet optional paper input tray
FH-1000	Filter holder (Germany only)
Carton Contents	Toner cartridge, drum, power supply cord, driver software for Windows®, Quick Set-Up Guide (PC interface cable NOT included)
	nables will vary depending on the complexity of the aper size, page per job, and the type of media.
Environment	
Power Consumption	Printing - 640W (390W in quiet mode), ready - 32W, sleep - 6.5W, deep sleep - 1.2W, off - 0.04W
TEC Value	1.763kWh / Week
Sound Pressure Level	Printing – 52dbA, quiet mode printing - 50dbA, ready – up to 34dbA
Sound Power Level	Printing – 6.9BA, quiet mode printing - 6.47BA, ready – up to 4.7BA
Power Saving	This enables the printer to consume less energy when not in use
Toner Saving	This reduces the toner usage and helps to reduce the total cost of printer ownership
Energy Star	Yes
Blue Angel	Yes
	Yes Yes





Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth. **www.brotherearth.com**



All specifications correct at time of publication, March 2016. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.